

711BPB | SMART DMM.



Description:

- Multimeter:
- SMART FUNCTION
- The multimeter automatically chooses the measurement to display
- UNIVERSAL POINTS
- thanks to the removable cap:
- Short points (CAT III) = safety for currents > 50V
- Long points (CAT II) = accessibility for currents < 50V
- 2 line display screen
- Directly displays Amps when used with FACOM Ammeter Clamps
- Min Max mode: ideal for measurements of sensors and probes
- Current clamp :
- Fits on FACOM multimeters type 711, 714, ...
- Allows non-contact current measurements
- Compatible with multimeters capable of measuring mV
- Multimeter:
- Voltmeter: AC / DC from 0 to 600 V
- Resistance measurement 10 MΩ and continuity
- Frequency meter: 0 to 3 kHz
- TRMS, CAT III, ETL / CE measurement
- delivered with 2 CAT II & CAT III touch points
- Current clamp :
- AC and DC AC current measurement
- AC / DC: 20 A 400 A
- AC / DC: 400 A 1500 A
- Diameter of the jaws: 53 mm
- Maximum diameter of cable 52 mm

- Category IV 600 Volts
- L. x W. x H.: 70 x 47x 155 mm.

	711BPB
Height H [mm]	155.0
Weight [g]	320.0